

www.itmikro.com





Features

- Microprocessor based numerical relay
- Current measurement based on fundamental
- Three-phase, low-set overcurrent
- Three-phase, high-set overcurrent
- Local display of measured and set values
- Definite time for low-set and high-set
- Non-volatile fault value recording
- Programmable relay outputs
- Complies with IEC 60255 standard
- ANSI Code: 50P, 51P

Technical Data

RATINGS

Rated current (In) :5A : 50 or 60 Hz Rated frequency

: < 0.3 VA at I_n Burden Thermal withstand : 4 x I_n continuous **ACCURACY**

Protection thresholds

: ± 5% with a Time delay

minimum of 50 ms

:±5%

INDICATORS

Auxiliary supply Pick-up

: Red indicator Trip

: Green indicator : 7-segment display

and Red indicators

AUXILIARY SUPPLY

Model NX234A-240A : 198 ~ 265 V AC : 94 ~ 127 V AC Model NX234A-110A : 50 or 60 Hz

Supply frequency VA rating : 3 VA typical

OUTPUT CONTACTS (R1 & R2)

Rated voltage : 250V AC / DC

Contact rating :5A

: 100,000 operations Expected electrical life at rated current

Expected mechanical life : 5 x 106 operations

ENVIRONMENTAL CONDITIONS

Temperature : -10°C to 55°C Humidity : 5% to 95%,

non-condensing

MECHANICAL

Mounting : Panel mounting : 96(w) x 96(h) x 110(d) Dimension (mm) Enclosure protection: IP54 at the panel

Approximate weight: 0.8 kg

SETTING RANGES

Low-set (I>) : 0.1 A to 10.0 A (2% to 200%)

Low-set definite time (t >) : 0.00 sec to 100 sec

: 0.5 A to 100 A (10% to 2000%) or disable High-set (I>>)


High-set delay time (t >>) : 0.00 sec to 100 sec

(0.00 to 1.00, step 0.01; 1.00 to 10.0, step 0.10; 10.0 to 100, step 0.5)




www.itmikro.com

Typical Application Diagram



Case Dimensions



Ordering Information

MODEL DESCRIPTION

NX234A - 240A For 50/60 Hz system, auxiliary supply 198 $^{\sim}$ 265 V AC NX234A - 110A For 50/60 Hz system, auxiliary supply 94 $^{\sim}$ 127 V AC